

LINEAR TRANSDUCERS with analogue output Series PNS-V • PN2S-V • PN231-V

- 50 to 950 mm strokes
- Excellent linearity
- Infinite resolution
- Easy mounting method
- M12 Connector
- IP65 protection degree

PNS-V	PN2S-V	PN231-V
Strokes: 50 to 950 mm • rod Ø 6 mm • radial connector	Strokes: 50 to 500 mm • rod Ø 6 mm • radial connector • two ball joints Ø 5 mm	Strokes: 50 to 750 mm • rod Ø 8 mm • radial connector • two ball joints Ø 8 mm

ELECTRICAL & OPERATING SPECIFICATIONS										
Series		PNS-V	<u>/</u>		PN2	S-V		P	N231-V	
Output signal			0÷10	V voltage	output p	roportion	al to the	position		
Supply voltage					18÷30	0 Vdc				
Strokes mm	50 •	100 •	150 •	200 •	250 •	300 •	400 •	500 •	750* •	950*
Linearity	±0.075% ±0.1%									
Resotution	Infinite									
 Mechanical life 	100 milion									
 Ripetibility 	<0.01 mm									
Connections	4-pin M12 male connector									
 Connector position 	Radial Radial Radial									

^{*}Stroke mm 750 available for series PNS-V, PN231V - Stroke mm 950 available for series PNS-V

MECHANICAL & ENVIRONMENTAL SPECIFICATIONS					
Series	PNS-V	PN2S-V	PN231-V		
Dimensions	See the drawing				
Materials: housing	And	odised aluminium with glass-filled	nylon flanges		
rod	Stainle	ss steel on self-lubricating bearing	gs – free rotation		
■ Rod Ø	6 mm	6 mm	8 mm		
Fixing	Fi	reely movable clamping brackets	or ball joints		
 Stem max linear speed 	5 m/sec				
 Sliding friction 		0.1 Kg – with return spring: 0	.5 Kg		
■ Vibration resistance (10÷2000 Hz)		15 g			
 Shock resistance (11 ms) 		50 g			
 Operating temperature 	-20 ÷ 80°C				
Stocking temperature	-30 ÷ 90°C				
 Protection degree 		IP65			

STROKES

		Ser	ies PNS-\	/ • PN2S-\	/ • PN231	-V				
NOMINAL STROKE mm	50 •	100 •	150 •	200 •	250 •	300 •	400 •	500 •	750* •	950*
ELECTRICAL STROKE Nominal stroke + 1 mm										
MECHANICAL STROKE Nominal stroke + 3 mm										
*Stroke mm 750 available for series PNS-V, PN231V - Stroke mm 950 available for series PNS-V										

CONNECTIONS


The electrical connection is granted by means of 4-pin M12 male connector. Flying part not included.



CONNECTION DIAGRAM	
PIN 1 = + OUT 0 : 10V	
PIN 2 = - OUT 0 : 10V	
PIN 3 = OV SUPPLY	
PIN 4 = + 18V : 30 VDC	

MOUNTING & OPTIONAL FITTINGS

The transducers are easily fastened by means of the provided **brackets**, which can be placed **freely along the body**. **Ball joints and self-aligning articulated joints** can be used **for air-fixing**, allowing to compensate mounting mis-alignments. The transducer series **PNS-V** can also be provided with **feeler pin**.





REF. M1040/ M1041/M1039

ORDERING INFORMATION

PNS-V	50	MR
	5750 type PNS-V only	,

Series PNS-V Ref M1269V








CORSA NOMINALE STROKE	×
50	190
100	240
150	290
200	340
250	390
300	440
400	540
500	640
750	890
950	1090

Series PN2S-V Rie M2170V

 \bigoplus_{Φ}









CORSA NOMINALE STROKE	х
50	187
100	237
150	287
200	337
250	387
300	437
400	537
500	637

Serie PN231-V Ref M1271V





CORSA NOMINALE STROKE	х
50	247
100	297
150	347
200	397
250	447
300	497
400	597
500	697
750	945



REFERENCES

Further information at:

Transducers PNS-V, PN2S-V, PN231-V https://www.elap.it/linear-potentiometers/pns-v-series/



